

SQUAWK DIRTY TO ME





IN CASE OF EMERGENCY SQUAWK 7700

- simple and effective 6hp stereo VCF
- 8 filter modes available with meta CV scanning, famous zero-delay feedback Grand Terminal filters
- additional hi-pass filter in series quickly cuts the boomy low end
- 48 kHz 16 bit digital audio stereo processing

Depth: 30mm (with plugged ribbon cable)

Power requirements: +12V: 120 mA
-12V: 15 mA



WARRANTY

RTFM – be so kind and read the manual. It will provide you with the information you need to fully indulge the module you just purchased – for which we like to thank you.

Enjoy your sound experiences, dear sonic traveller.

Beginning from the product's purchase date a 1-year warranty is guaranteed for each product in case of any manufacturing errors or other functional deficiencies during runtime.

The warranty does not apply in case of:

- damage caused by misuse
- mechanical damage arising from careless treatment (dropping, vigorous shaking, mishandling, etc.)
- damage caused by liquids or powders penetrating the device
- heat damage caused by overexposure to sunlight or heating
- electric damage caused by improper connecting

The warranty covers replacement or repair, as decided by us. Please contact us via email for a return authorization before sending anything. Shipping costs of sending a module back for servicing is paid by the customer.

Device complies with all EU regulations concerning RoHS lead-free manufacturing and WEEE disposal

Endorphin.es are made in Barcelona, Spain

Visit us:

<http://endorphin.es>

<https://youtube.com/user/TheEndorphines>

<https://facebook.com/TheEndorphines>

<https://www.instagram.com/endorphin.es/>

Drop us a line:

info@endorphin.es

FURTH BARCELONA, S.L.

VAT ID:ES B66836487

FIRMWARE UPDATE

Download latest firmware/bank when available from:
<http://airways.endorphin.es>

Power OFF your modular system:




Hold 'mode' while powering your system again:



You will see status LED will blink blue:



Connect the audio output from your computer headphones output to one of the audio inputs of the module with simple mono or stereo cable




Press PLAY and wait 1.5 minutes. The module will reboot automatically after the new firmware was installed



Make sure you don't input any extra sounds during update process (reminder signals from your calendar, etc.). When status LED flashes RED – that means signal is too low or too high – just reset the firmware acquire process by pressing MODE once.





FILTER MODES



Pressing the 'mode' button shortly cycles thru all 8 filter mode.




When LED is semi LIT, it shows one of V...IV chosen filter modes. When LED is full LIT, it shows one of I...IV chosen filter modes.

Only one filter mode (type) available at once.


- I** • 24 DB/OCT TRANSISTOR LADDER zero-delay feedback low-pass filter: Modelled after the famous Minimoog filter.
- II** • MS-20 12 DB/OCT zero-delay feedback OTA-low-pass filter: Be careful, that filter has very powerful and dirty resonance.
- III** • 12 DB/OCT LO-PASS GATE, non-resonant zero-delay feedback filter where instead of the resonance, we control the DECAY closing time of the virtual vactrol. While 'pinging' Cutoff CV with a short pulse of voltage and adjusting the decay will give us that distinct 'Buchla Bongo' sound.
- IV** • 12 DB/OCT RESONANT LO-PASS GATE – variation of the zero-delay feedback vactrol filter model III with fixed fast decay and full control over the resonance. The resonance of the sound is ringing, just as it may be expected from a typical LPG.

- V** • 12 DB/OCT DJ ISOLATOR-STYLE BIPOLAR zero-delay feedback state-variable filter: Sound is unfiltered when the Cutoff knob is in the middle/noon position. It filters high frequencies/low-pass, when turning the knob CCW and filters low frequencies/hi-pass, when turning the knob CW from its middle position.
- VI** • 12 DB/OCT HIGH-PASS STATE-VARIABLE FILTER: (zero delay feedback), single hi-pass on full knob range
- VII** • 12 DB/OCT BAND-PASS STATE VARIABLE zero-delay feedback filter with 'cutoff' knob you choose band's centre point and with Resonance knob the width of the band.
- VIII** • COMB FILTER: It recreates a series of harmonically related amounts of notch filters. In static state, it sounds similar to a phaser, but with modulation applied to the frequency it comes closer to a flanger.


SIMPLE MONO OPERATION




MONO TO STEREO OPERATION




TRUE STEREO OPERATION



QUICK AND DIRTY PATCH EXAMPLE



META META META META META META META META



ENDORPHIN.ES® – SQUAWK DIRTY TO ME
Module design by Andreas Zhukovsky
Collection Spring/Summer 2019
Made in Barcelona

Special thanks to Xavier Galai for additional code and crazy ideas.

Follow, like, post and tag us at instagram:
@endorphin.es
or contact us:
info@endorphin.es