
ULTRA CHORUS UC200

Ultimate Stereo Chorus Effects Pedal

Thank you for showing your confidence in us by purchasing the BEHRINGER ULTRA CHORUS UC200. This ultimate effects pedal is designed to deliver super-thick chorus with unbelievable stereo effect. Thanks to its high-performance features you'll have full parameter control for absolute flexibility and limitless creative options.

The chorus effect slightly detunes the original signal. A very pleasant detune effect is created in connection with the pitch variation. The chorus effect is used often and quite extensively used for dispersing signals.

1. Controls



- 1 The **LEVEL** control adjusts the output level.
- The TONE control allows you to adjust the overall effects sound and achieve a more defined and brilliant tone.
- 3 The **RATE** control determines the chorus effect speed.
- 4 Turn up the **DEPTH** control to achieve a fuller, deeper effect sound.
- The **ON/BATT** LED illuminates when the effect is activated. It also serves as a battery level indicator.
- 6 Use the footswitch to activate/deactivate the effect.
- Use this ¼" TS **IN** connector to plug in the instrument cable.
- The two ¼" TS connectors OUT A and OUT B send the signal to your amp. Use both connectors if you want to achieve full stereo chorus effect. For mono use just plug in OUT A.

Use the **DC IN** connection to plug in a 9 V power supply (not included).

The **BATTERY COMPARTMENT** is located underneath the pedal cover. To install or replace the 9 V battery, press the hinges with a ballpen and remove the pedal cover. Be careful not to scratch the unit.



The UC200 has no on/off switch. As soon as you insert the jack into the in connector, the UC200 begins running. When not using the UC200, remove the jack from the in connector. This extends the life of the battery.

The **SERIAL NUMBER** is located at the bottom.

2. Safety Instructions

Do not use near water, or install near heat sources. Use only authorized attachments/accessories. Do not service product yourself. Contact our qualified servicing personnel for servicing or repairs, especially when power supply cord or plug is damaged.

3. Warranty

Please register your new BEHRINGER equipment right after your purchase by visiting http://behringer.com and read the terms and conditions of our warranty carefully.

4. Specifications

1⁄4" TS
500 kΩ
1⁄4" TS
1 kΩ
1⁄4" TS
1 kΩ
9 V →, 100 mA regulated
120 V∼, 60 Hz
220 V∼, 50 Hz
240 V∼, 50 Hz
230 V∼, 50 Hz

Power connector	2 mm DC jack, negative center
Battery	9 V type 6LR61
Power consumption	30 mA

Physical/Weight	
Dimensions	approx. 2 1/8 x 2 3/4 x 4 4/5"
(H x W x D)	approx. 54 x 70 x 123 mm
Weight	approx. 0.73 lbs / 0.33 kg

BEHRINGER is constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to time to existing products without prior notice. Specifications and appearance may therefore differ from those listed or shown

TECHNICAL SPECIFICATIONS AND APPEARANCES ARE SUBJECT TO CHANGE WITHOUT NOTICE AND ACCURACY IS NOT GUARANTEED. BEHRINGER IS PART OF THE MUSIC GROUP (MUSIC-GROUP.COM.). ALL TRADEMARKS ARE THE PROPERTY OF THEIR RESPECTIVE OWNERS. MUSIC GROUP ACCEPTS NO LIABILITY FOR ANY LOSS WHICH MAY BE SUFFERED BY ANY PERSON WHO RELIES EITHER WHOLLY OR IN PART UPON ANY DESCRIPTION, PHOTOGRAPH OR STATEMENT CONTAINED HERRIC. COLORS AND SPECIFICATIONS MAY VARY FROM ACTUAL PRODUCT. MUSIC GROUP PRODUCTS ARE SOLD THROUGH AUTHORIZED FULLFILLERS AND RESELLERS ONLY. FULLFILLERS AND RESELLERS ARE NOT AGENTS OF MUSIC GROUP PAND HAVE ABSOLUTELY NO AUTHORITY TO BIND MUSIC GROUP BY ANY EXPRESS OR IMPLIED UNDERTRAING OR REPRESENTATION. THIS MANUAL IS COPYRIGHTED. NO PART OF THIS MANUAL MAY BE REPRODUCED OR TRANSMITTED IN ANY FORM OR BY ANY MEANS, ELECTRONIC OR MECHANICAL, INCLUDING PHOTOCOPYING AND RECORDING OF ANY KIND, FOR ANY PURPOSE, WITHOUT THE EXPRESS WRITTED IN AUTHORISE CROUP IP LTD. ALL RIGHTS RESERVED. © 2012 MUSIC Group IP Ltd. Trident Chambers, Wickhams Cay, P.O. Box 146, Road Town, Tortola, British Wirgin Islands

